

Program Timer

PW-6242B



OVERVIEW

PW-6242B is a program timer device that users can set a certain date and time to perform a scheduled broadcast in 6000 system. A user can upload or download the files in PC to the inserted SD card by connecting a USB cable, and also can copy the sound source stored in the USB memory to the SD card. In addition, scheduler set up can be easily done through a management program by connecting PC.

FEATURES

- ❖ Considering user convenience
- ❖ Adopting large vacuum fluorescent display
- ❖ Programing using PC
- ❖ Various melodies and voices output
- ❖ Hosting using USB terminal
- ❖ Key lock
- ❖ BACK-UP power
- ❖ Blackout measurement
- ❖ Automatic return
- ❖ AC Power output control
- ❖ AC Power output time control

SPECIFICATIONS

	PW-6242B
Input Channel	5CH
Output Channel	4CH
Output Level (1kHz 0dBFS MP3 Play, Volume Max)	Maximum +15dBu
Frequency Response	20Hz~20kHz
S/N (20kHz LPF)	More than 100dB
THD (20kHz LPF)	Less than 0.05%
AC Power Output1	Maximum 500W
AC Power Output2	Maximum 500W
Data Retention Time	Maximum 12 days
Melody Time (TR0001~TR0015) Total 15 melodies - 247 seconds	TR no.1-2 sec, TR no.2-3 sec, TR no.3-3 sec, TR no.4-5 sec, TR no.5-5 sec, TR no.6-7 sec, TR no.7-7 sec, TR no.8-10 sec, TR no.9-10 sec, TR no.10-15 sec, TR no.11-20 sec, TR no.12-30 sec, TR no.13-30 sec, TR no.14-40 sec, TR no.15-60 sec
Operating Temperature	-10°C~+40°C
Power Source	AC 220-240V, 50/60Hz, DC 24V
Power Consumption	1000W
Weight (set)	4.57kg/10lb
Dimensions (set)	482(W)×88(H)×280(D)mm/19(W)×3.5(H)×11(D)in

* Design and specification are subject to be changed for the improvement of product quality without pre notice.

interM

Inter-M Corporation

- Office : 719, DOBONG-RO, DOBONG-GU, SEOUL, KOREA
- Tel : +82-2-2289-8140~8, Fax : +82-2-2289-8149
- Home page : <http://www.inter-m.com>, E-mail : overseas@inter-m.com

Inter-M Corporation (USA)

- Office : 5666 CORPORATE AVE. CYPRESS, CA 90630
- Tel : +1-714-828-2200, Fax : +1-714-828-2210
- Home Page : <http://www.inter-m.net>, E-mail : info@inter-m.net

PROGRAM TIMER